



Tradition & Performance

With more than 100 years of experience, A&M hearing offers capable hearing solutions that help people in their day-to-day listening situations so that they can retain their active lifestyle. At A&M we focus on the substantial: providing well-proven digital hearing aids that everybody can use.

A&M is a brand of
Sivantos GmbH
Henri-Dunant-Strasse 100
91085 Erlangen
Germany

Order No. 80235-99CI-7600 | Printed in Germany
© 05/2018 Sivantos

am-hearing.com



Hearing Instrument Portfolio Overview

Spring 2018

am-hearing.com

Hearing Instrument Portfolio Overview

Type	XTM RIC P8	XTM S P8	XTM M P8	XTM P P8	XTM XP P8	XTM IF CIC P8	XTM Custom P8	XTM S P6 *	XTM M P6 *	XTM P P6 *	XTM XP P6	XTM IF CIC P6	XTM IF ITC P6	XTM Custom P6 *	XTM S P4	XTM P P4	XTM XP P4	XTM IF CIC P4	XTM IF ITC P4	XTM S A4 **	XTM P A4	XTM XP A4	XTM IF CIC A4	XTM IF ITC A4	STF P T3	STF XP T3	STF P T1
Product details																											
Matrix (2 cc) ¹	S 45/108 dB M 60/119 dB P 70/124 dB HP 75/130 dB	45/124 dB 55/124 dB	53/126 dB 60/130 dB	65/129 dB 70/131 dB 77/135 dB	82/140 dB	50/113 dB	50/113 dB 55/118 dB 65/124 dB	45/124 dB 55/124 dB	53/125 dB 60/130 dB	70/134 dB	80/140 dB	50/113 dB	55/116 dB	50/113 dB 55/118 dB 65/124 dB	45/124 dB 55/124 dB	70/134 dB	80/140 dB	50/113 dB	55/116 dB	45/124 dB 55/124 dB	70/132 dB	79/140 dB	50/113 dB	55/116 dB	70/132 dB	79/140 dB	62/130 dB
Battery size	312	312	13	13	675	10	10 312 13	312	13	13	675	10	312	10 312 13	312	13	675	10	312	312	13	675	10	312	13	675	13
Power consumption ¹	1.1 mA	0.9 mA	1.1 mA	1.6 mA	2.1 mA	1.1 mA	1.1 mA	0.9 mA	1.0 mA	1.4 mA	2.4 mA	1.1 mA	1.0 mA	1.1 mA	0.9 mA	1.4 mA	2.4 mA	1.1 mA	1.0 mA	0.9 mA	1.3 mA	2.2 mA	1.1 mA	1.0 mA	1.2 mA	2.2 mA	1.2 mA
Fitting mode	AMFit 8	AMFit 8	AMFit 8	AMFit 8	AMFit 8	AMFit 8	AMFit 8	AMFit 8	AMFit 8	AMFit 8	AMFit 8	AMFit 8	AMFit 8	AMFit 8	AMFit 8	AMFit 8	AMFit 8	AMFit 8	AMFit 8	Fit2Go App	Fit2Go App	Fit2Go App	Fit2Go App	Fit2Go App	Toggle Fit	Toggle Fit	Toggle Fit
Features																											
Frequency channels/ Compression controls	16/8	16/8	16/8	16/8	16/8	16/8	16/8	12/6	12/6	12/6	12/6	12/6	12/6	12/6	8/4	8/4	8/4	8/4	8/4	8	8	8	8	8	4	4	2
Hearing programs	4	4	4	4	4	4 ²	4	4	4	4	4	4 ²	4	4	4	4	4	4 ²	4	6 preconfigured sound profiles	6 preconfigured sound profiles	6 preconfigured sound profiles	6 preconfigured sound profiles	6 preconfigured sound profiles	4 preconfigured sound profiles	4 preconfigured sound profiles	3 preconfigured sound profiles
Volume control	o ³	–	o ³	o ³	•	–	o ⁴	–	o ³	•	•	–	–	o	–	•	•	–	–	–	•	•	–	–	•	•	•
Push button	o ³	•	o ³	o ³	•	–	o	•	o ³	•	•	–	•	o	•	•	•	–	•	–	–	–	–	–	–	–	–
Telecoil	•	–	•	•	•	–	o ⁴	–	•	•	•	–	–	o ⁴	–	•	•	–	–	–	–	–	–	–	–	–	–
Battery door on/off function	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•
Audio input	–	–	o ⁵	o ⁵	o ⁵	–	–	–	o ⁵	o ⁵	o ⁵	–	–	–	–	o ⁵	o ⁵	–	–	–	–	–	–	–	–	–	–
Modifications																											
Color conversion kit	o	o	o	o	o	–	–	o	o	o	o	–	–	–	o	o	o	–	–	o	o	o	–	–	o	o	–
Accessories																											
Programming adapter/pill	Size 312	Size 312	Size 13	Size 13	CS44	Flex connector	Flex connector	Size 312	Size 13	Programming shoe 13	Programming shoe 675	Flex connector	Flex connector	Flex connector	Size 312	Programming shoe 13	Programming shoe 675	Flex connector	Flex connector	–	–	–	–	–	–	–	–
Wireless programming via ConnexxAir	•	•	•	•	•	•	o	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–
Compatible fitting set	Click domes and Click sleeves	ThinTube / Earhook	S-Tube / Earhook	S-Tube / Earhook	Earhook	Click domes and Click sleeves	–	ThinTube / Earhook	ThinTube / Earhook	Comfort coupling	Comfort coupling	Click domes and Click sleeves	Click domes and Click sleeves	–	ThinTube / Earhook	Comfort coupling	Comfort coupling	Click domes and Click sleeves	Click domes and Click sleeves	ThinTube / Earhook	Comfort coupling	Comfort coupling	Click domes and Click sleeves	Click domes and Click sleeves	Comfort coupling	Comfort coupling	Simple coupling
Smart Connect	o	o	o	o	o	o	o	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–	–
Smart Key	o	o	o	o	o	o	o	–	–	–	–	–	–	–	–	–	–	–	–	o	–	–	–	–	–	–	–
Smart Remote App	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	•	–	–

¹ Max. values

² Via Smart Remote App or Smart Key

³ Via programmable Rocker Switch

⁴ Not available for CIC

⁵ With battery compartment modification

• Standard

o Optional

* updated with Smart Remote App & automatic directional microphones (BTE only)

** available in June 2018